

Mini Fast / Gigabit Ethernet PoE+ Media Converter

10/100/1000Base-T PoE+ RJ-45 Port + 100/1000Base-X SFP Slot



This Gigabit Ethernet Stand-alone Mini Media Converter provides cost-effective media conversion between 10/100/1000Base-T ports and 100/1000Base-SX/LX ports. With its fixed configuration, deployments are just plug-and-play, and its small size makes it ideal for locations where space is limited. Operating at Layer 2, the data link layer, this converter not only converts copper to fiber, but it also provides rate conversion allowing legacy 10/100 copper devices to connect to 1000Base-SX/LX fiber.

In addition to providing copper to fiber conversion, this converter is also classified as Power Sourcing Equipment (PSE), meaning it combines data received over the fiber optic link with 56VDC input power to provide power and data to a Powered Device (PD) over the twisted Pair cable, while complying with the IEEE 802.3af and IEEE 802.3at PoE+ standards. This allows the user to take advantage of the benefits of fiber cabling, along with the benefits of Power-over-Ethernet (PoE) technology.

Supporting PoE allows this converter to send data and power to devices like VoIP Phones, Security Cameras, and Wireless Access Points, especially if they need to be located in remote areas of your network that can only be reached with fiber optic cabling.

Ordering Information

M/GE-PSW-PSE-01
10/100/1000Base-T PoE+ RJ-45 port
[100 m/ 328 ft.]
to 100/1000Base-X SFP slot (empty)

Optional Accessories (sold separately)

SFP Modules

Mounting Options (sold separately)

WMBM

Wall Mount Bracket for Mini

DRBM

DIN Rail Mount Bracket for Mini

RMBM

Rack Mount Bracket for Mini, use with RMS19-SA4-02

Note: Cannot be used with M-MCR-01 or E-MCR-05 Racks due to power limitations

Features

- Wall mount, DIN Rail, or table top installation
- External AC/DC power supply included with country specific power cord
- 2-port 10/100/1000 copper to fiber media conversion with IEEE 802.3at PoE+ on the copper port
- Supports full 30 Watts of power to the twisted pair port
- SFP slots can support any 100Base-FX or 1000Base-X fiber SFP module
- Supports Auto-Negotiation
- Supports Auto-MDI/MDIX
- **Active Link Pass Through (ALPT)**
 - Automatically detect the loss of Receive (Rx) signals on either fiber or copper port and propagate the failure to the end devices
- **Auto Power Reset**
 - Re-set the power to the end PD device during a Link Pass Through (LPT) event, ensuring it is ready to go when the fault is corrected

Specifications

Standards	IEEE 802.3-2012 IEEE 802.3af/at PSE-PoE IEEE 802.3ab IEEE 802.3z IEEE 802.3x IEEE 802.3az
Switch Features	Max Packet Size 10,000 bytes Max MAC Addresses 8k 1Mbit shared buffer memory
Status LEDs	PWR On (green) = Power to converter PoE Off = No PD detected On = AF mode or AT mode Top LED TP Status Bottom LED Fiber Status
Dimensions	Width: 1.8" [46 mm] Height: 0.85" [22 mm] Depth: 3.3" [85 mm]
Power Consumption	34W with full IEEE 802.3at 30 Watt load
Power Source	External AC/DC 56VDC, 40W power adapter
Power-over-Ethernet	Max PoE Budget: 30 Watts
Environment	Operating: 0°C to +40°C (with included power supply) Storage: -40°C to +85°C Humidity: 5% to 95% (non-condensing) Altitude: 0 – 10,000 ft.
Weight	2 lbs. [0.9 kg]
MTBF	M/GE-PSW-PSE-01 only 2,941,024 hours (Telcordia SR-332) Included Power Supply only (25173) 159,357 hours (MIL-DHBK-217F)
Certifications	EN55032-2012 Class A, IEC 61850-3:2002, EN55024-2010, CE Mark, Power Supply is UL listed
Warranty	Lifetime

Power Supply Included

To order the corresponding country specific power supply, add the extension from the list below to the end of the SKU;
Ex: M/GE-PSW-PSE-01-NA

-NA = Country Code

- NA = North America
- LA = Latin America
- EU = Europe
- UK = United Kingdom
- SA = South Africa
- JP = Japan
- OZ = Australia
- BR = Brazil

Features Continued

- Jumbo frame support
- 8K MAC address table
- LEDs indicators for power status, Link/Activity per port, & PoE status/classification
- Plug-and-Play fixed configuration, no dip-switches
- Over-current protection
- Under-current protection
- Fault protection input